



SAT

★★★
PROFESSIONAL



SAT Multi Switch (5 > 8)

This SCHWAIGER® multi switch is used to distribute digital signals of 1 satellite position to up to 8 subscribers. You can feed signals from a Quad or Quattro LNB as well as terrestrial signals. All subscribers can make use of

the entire range of programmes independently from one another.



ARTICLE INFORMATION

Article Nr
EAN

SEW4058 531
4004005405842



4 004005 405842

Last updated: 23.03.2016



FEATURES (SEW4058 531)

- multi switch distributes 1 satellite position to 8 outputs
- can be fed with terrestrial signals (e.g. DVB-T or radio stations)
- independent reception of all available programmes for every subscriber
- suitable for use with Quad and Quattro LNBs

TECHNICAL DATA

quality	** Professional
Point of use	indoor use
Connections (input)	4x F jack (SAT) 1x F jack (TV/FM)
Connections (output)	8x F jack (SAT)
Output level (max.)	(typ.) 100 dBµV (SAT) (typ.) 85 dBµV (TV/FM)
Frequency range	950 - 2150 MHz (SAT) 47 - 862 MHz (TV/FM)
Isolation	30 dB
Changeover	13/18V/22KHz
Transmission loss	(typ.) 8 dB (SAT) (typ.) 1 dB (TV/FM)

Power consumption	through LNB (max.) 600 mA
Power supply	230 V AC , 50 Hz
Power consumption	max. 35 W
Operating temperature	-10 bis +50 °C
Power supply unit	integrated
Weight (set)	device 750 g
Dimensions (width)	360 mm
Dimensions (depth)	58 mm
Dimensions (height)	120 mm
packaging	clamshell SF

Last updated: 23.03.2016